

AD-A070 409

ARMY ELECTRONICS RESEARCH AND DEVELOPMENT COMMAND WS--ETC F/6 17/1
EFFECTS OF ARRIVAL TIME ERRORS IN WEIGHTED RANGE EQUATION SOLUT--ETC(U)
APR 79 D M SWINGLE

UNCLASSIFIED

ERADCOM/ASL-TR-0029

NL

| OF |
AD
A070409



ASL-TR-0029

AD

Reports Control Symbol
OSD - 1366

LEVEL

12

AD A 070 409

EFFECTS OF ARRIVAL TIME ERRORS IN WEIGHTED RANGE EQUATION SOLUTIONS FOR LINEAR BASE SOUND RANGING

THIS DOCUMENT IS BEST QUALITY PRACTICABLE.
THE COPY FURNISHED TO DDC CONTAINED A
SIGNIFICANT NUMBER OF PAGES WHICH DO NOT
REPRODUCE LEGIBLY.

APRIL 1979

By

DONALD M. SWINGLE



DDC FILE COPY

Approved for public release; distribution unlimited



US Army Electronics Research and Development Command
Atmospheric Sciences Laboratory

White Sands Missile Range, NM 88002

79 06 25 017

NOTICES

Disclaimers

The findings in this report are not to be construed as an official Department of the Army position, unless so designated by other authorized documents.

The citation of trade names and names of manufacturers in this report is not to be construed as official Government indorsement or approval of commercial products or services referenced herein.

Disposition

Destroy this report when it is no longer needed. Do not return it to the originator.

DISCLAIMER NOTICE

**THIS DOCUMENT IS BEST QUALITY
PRACTICABLE. THE COPY FURNISHED
TO DDC CONTAINED A SIGNIFICANT
NUMBER OF PAGES WHICH DO NOT
REPRODUCE LEGIBLY.**

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER ASL-TR-0029	2. GOVT ACCESSION NO.	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) EFFECTS OF ARRIVAL TIME ERRORS IN WEIGHTED RANGE EQUATION SOLUTIONS FOR LINEAR BASE SOUND RANGING.	5. TYPE OF REPORT & PERIOD COVERED R&D Technical Report	
7. AUTHOR(s) Donald M. Swingle	6. PERFORMING ORG. REPORT NUMBER	
9. PERFORMING ORGANIZATION NAME AND ADDRESS Atmospheric Sciences Laboratory White Sands Missile Range, NM 88002	8. CONTRACT OR GRANT NUMBER(s)	
11. CONTROLLING OFFICE NAME AND ADDRESS US Army Electronics Research and Development Command Adelphi, MD 20783	10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS DA Task No. 1L16211AH-71-26	
14. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office) Research and development technical rept.	12. REPORT DATE Apr 1 1979	
	13. NUMBER OF PAGES 47	
	15. SECURITY CLASS. (of this report) UNCLASSIFIED	
16. DISTRIBUTION STATEMENT (of this Report) Approved for public release; distribution unlimited.		
17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report) ERADCOM/ASL-TR-0029		
18. SUPPLEMENTARY NOTES 1L162114AH71 26		
19. KEY WORDS (Continue on reverse side if necessary and identify by block number) Meteorology Target acquisition Sound ranging Errors		
20. ABSTRACT (Continue on reverse side if necessary and identify by block number) Results of the research discussed in this report show that the errors in target location computed by the Weighted Range Equation Solution, when applied to a regular, linear, six-microphone array, are approximately proportional to the errors in arrival time, relative to the assumptions inherent in the solution model. For most target locations, microphones 2 and 5, in the six-microphone array, are relatively less influential in determining target location than are microphones 1, 3, 4, and 6. The transfer function between arrival time errors		

DD FORM 1 JAN 73 1473 EDITION OF 1 NOV 65 IS OBSOLETE

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

410663

79 06 25 017

20. ABSTRACT (cont)

at one or more microphones is shown to be approximately linear and to possess the property of superposability; i.e., the combined effect of several errors in arrival time is approximately equal to the sum of the effects of each error taken as occurring alone. Several general properties of symmetry and anti-symmetry are demonstrated.

This report provides its readers with the basic vector error response of the Weighted Range Equation Solution for all areas in which the AN/TNS-10 Sound Ranging Set is effective.

Accession For	
NTIS GIN&I	<input checked="" type="checkbox"/>
DDC TAB	<input type="checkbox"/>
Unannounced	<input type="checkbox"/>
Justification	
By	
Distribution	
Availability	
Dist	Available for special
A	23012

CONTENTS

	<u>Page</u>
INTRODUCTION	2
DATA PRESENTATION	5
DATA INTERPRETATION	5
EFFECT OF UNIT INPUT ERRORS ON SOLUTIONS	6
LINEARITY OF ERROR TRANSFER FUNCTIONS	7
SUPERPOSABILITY OF ERROR TRANSFER FUNCTIONS	7
CONCLUSIONS	8
FIGURE	10
TABLES	11
REFERENCES	34
APPENDIX	
THE WEIGHTED RANGE EQUATION SOLUTION	35

INTRODUCTION

Linear base sound ranging, using the GR-8 or AN/TNS-10 Sound Ranging Set, has been shown to be an effective means for locating enemy firing batteries which are beyond the range of direct visual observation. Development of the USRAN3 solution technique by Swingle, Bellucci, and Crenshaw showed that the present system was not performing to the limits of its accuracy potential. Their evaluations showed that an improvement in accuracy from 2.2 percent of range* to 1.8 percent could be achieved by a simple change in the method by which the final target location (fix) was computed.^{1,2} They noted that further improvements were believed to be achievable.

In response to a request from US Army Materiel Command Headquarters in June 1974, Swingle developed an error analysis for the overall system which was used to estimate the likely improvement which could be achieved for a typical target located centrally to the microphone array and 10,000 meters ahead thereof. This restriction of target location was adopted for reasons of both simplicity and nonavailability of quantitative error sensitivity data for other locations.

The present report covers the first steps in expanding that analysis to include the entire field of potential target locations, including extension of the analysis to points beyond the usual range of sound ranging utility, i.e., to ranges exceeding twice the base length and to flanking angles beyond 15 degrees from the normal of the outlying subbases.

This analysis will develop the ultimate accuracy which can be expected from a variety of sound ranging array configurations having tactical practicality, including, of course, the six-microphone "linear base" system with which the US Army is now equipped. Optimized meteorological correction methods, which take account of the natural variability of the atmosphere, will be considered as parts of the overall sound ranging system input error source.

It will be assumed that the reader is generally acquainted with the principles of sound ranging on artillery weapons based on the use of the AN/TNS-10 or similar system. All six microphones will be assumed to be installed along a straight base at uniform spacings of four sound seconds (about 1350 meters). While solutions for shot time and shot coordinates are unique, within the usual assumptions of an atmosphere having uniform

*Distance target is forward of line of microphones

¹Donald M. Swingle, Craig M. Crenshaw, and Raymond Bellucci, 1972, "Improved Sound Ranging Location of Enemy Artillery," Army Science Conference, US Military Academy, West Point, NJ

²Donald M. Swingle and Raymond Bellucci, 1973, "Improved Sound Ranging Location of Enemy Artillery," R&D Technical Report ECOM-5486, US Army Electronics Command, Fort Monmouth, NJ

wind and uniform temperature (sound speed), when arrival times from only three microphones are used to determine target location, the system is over-determined when more than three arrival times are used. Under these conditions a number of solution methods can be used, yielding generally different target locations.

Following the development and evaluation of the USRAN3 solution, Crenshaw and Swingle engaged in a continuing verbal and correspondence exchange,^{3,4} looking forward to a more general and even more accurate solution and meteorological correction method. This led to the evolution of the Weighted Range Equation Solution (WRAS) which is outlined in the appendix. In brief, this method determines the shot time and coordinates which minimize the sum of the squares of the differences between the square of the geometric range from solution point to each microphone and the square of the "propagation range" computed from the speed of sound along that direction and the difference between computed shot time and measured arrival time.

$$\sum_{i=1}^N W_i \times (R_i^2 - P_i^2)^2 = \text{minimum} \quad (1)$$

where W_i is a weighting factor which may be varied by any desired rule across the microphone array. A simple form for the W_i which was suggested by the known behavior of atmospheric variability as studied by Arnold and Bellucci⁵ and later by Lowenthal and Bellucci⁶ is

$$W_i = R_i^n / \sum_{i=1}^N R_i^n \quad (2)$$

³Personal communications between Dr. Craig M. Crenshaw and Dr. Donald M. Swingle, June 1972-December 1973

⁴Craig M. Crenshaw, 1972, "Sound Ranging Calculations," AMC Chief Scientist Technical Note Number 1, US Army Materiel Command, Alexandria, VA

⁵A. Arnold and R. Bellucci, 1957, "Variability of Ballistic Meteorological Parameters," Technical Memorandum M-1913, US Army Signal Engineering Laboratories, Fort Monmouth, NJ

⁶Marvin J. Lowenthal and Raymond Bellucci, 1970, "Variability of Ballistic Winds, R&D Technical Report ECOM-3259, US Army Electronics Command, Fort Monmouth, NJ

where n is any real number. Experimentation was conducted with n ranging from 0 to -10. When applied to actual sound ranging data, $n = -5$ generally gave the most accurate target locations. In the present study this weighting was used, but the conclusions are equally valid when solutions are computed using $n = 0$.

Earlier studies of sound ranging system error sensitivity had been conducted by Fox,⁷ Lee,⁸ and Bellucci.^{9,10}

All the above utilized solutions depended upon use of differences in arrival time at adjacent microphones. Fox used a least squares minimization of the differences between "true" and perturbed arrival time differences, while Lee minimized the squared differences between "true" and perturbed arrival times. Bellucci used the standard artillery solution. Bellucci's published work was confined to a set of only 12 points in the target area. Lee expressed errors as radial errors (i.e., miss-distance), thus precluding consideration of the vector nature of the error patterns. Fox considered radial and tangential errors relative to the center of the microphone array. Lee presented total radial error contours but provided no data on vector error. None of the researchers provided a dense, ordered array of errors at target points throughout the battle area which might be utilized for error analysis of both current and future tactical sound ranging systems.

Results obtained herein are in generally good agreement with these studies. They differ in that they present error transfer properties of the WRAS solution in terms of along-array and along-normal components. They also extend the range of the computations to at least five sound base (25 subbase) lengths ahead of the array and to 9 to 18 subbase lengths to either side of the centerline of the array. Additional computations, not covered in detail here, extend the computations out as far as 15 sound base (75 subbase) lengths forward of the array. The properties of linearity and superposability discussed below were also found to extend to such ranges, although

⁷H. L. Fox, 1968, "Meteorological Techniques for Sound Ranging; Theory of Errors," Technical Report ECOM-0233-2, US Army Electronics Command, Fort Monmouth, NJ

⁸Robert P. Lee, 1972, "Artillery Sound Ranging Computer Simulations," R&D Technical Report ECOM-5441, US Army Electronics Command, White Sands Missile Range, NM

⁹Raymond Bellucci, 1966, "Studies of Meteorological Techniques for Sound Ranging: Report II, Error Analysis," Technical Report ECOM-2703, US Army Electronics Command, Fort Monmouth, NJ

¹⁰Personal communications between Raymond Bellucci and Dr. Donald M. Swingle, June 1966-June 1972

errors were generally much larger. These results will be utilized in succeeding reports dealing with errors in microphone position and atmospheric input as well as terrain effects and sound ranging system improvement.

DATA PRESENTATION

The data of this report are uniformly presented as fields of numerical values, to provide, in a reasonably compact form, the detailed information required to assess the effects of various error sources on target location. Those readers whose taste leads to the representation of data in contour maps are invited to add their own analyses of the numerical fields presented. Both horizontal components of target location error are presented at each grid point to facilitate ready analysis of the vector character of the target location error associated with input data errors.

DATA INTERPRETATION

Figure 1 provides a schematic guide to interpretation of the following tables. Tables 1 through 23 provide the field of target location errors due to specified errors in arrival time at given microphones for each of a regular array of assumed "true" target locations. The targets are assumed to be at the points indicated by "+" (except along the left-hand edge of the figure).

These points are uniformly spaced by one subbase length forward of the center of each subbase and laterally from the center of the array. To the left of each target point appear two figures. The upper number is the error in meters which would arise in the solution by WRAS for the target along the X- or along baseline direction, while the lower number is the error in the Y- or normal-to-baseline direction.

Along the top of each figure are listed the subbase length (BL) in sound seconds (4 sound seconds is approximately 1350 meters) and the index number of the perturbed microphone (IP, counting from left to right as one faces the target from the baseline). In this report IP will range from 1 to 6. If two digits are given under IP, these digits indicate the two microphones whose arrival times are simultaneously perturbed. ID is used to indicate the perturbed parameter and will always be 8 in this report, indicating that the perturbation considered is in time of arrival at the microphones indicated by IP. The number of subbase lengths to the right of the array center which characterizes the top row of targets (+) is given by M. As the computations progress down the page, M is incremented for each row and appears at the left-hand edge of the paper abreast of the Y-component of error. Just above these changing values of M appears the value of IP given in the heading line. This value appears just to the left of the first + in each row which marks the point which is M subbase lengths from the array center. In all of the tables N = 25, indicating that the right-most + or target position in each row is 25 subbase lengths

forward of the microphone array. DXY indicates the spacing in both X and Y directions of the grid points in units one subbase long. In all tables herein DXY is 1.000. UP gives the assumed unit perturbation which is applied to the arrival time of the identified microphone(s) expressed in milliseconds. IW is the weighting exponent. In terms of equation (2), $n = -IW$. IW will always be 5 herein. ZZ gives the target height above the plane containing the microphones and is always 0.0 in this report. V1, V2, and V3 are the X-, Y-, and Z- components of the mean wind assumed in the computation, and will remain 0.00 in this report. Finally, TE is the assumed "effective temperature" for sound ranging, assumed to be 10°C herein.

Where **** appears on the tables, the error exceeds ± 999.5 meters, while -0+ appearing in the upper and lower left corners indicates that computations were not made for the point because it occurs at a large flanking angle ($|M| > N + 3$).

EFFECT OF UNIT INPUT ERRORS ON SOLUTIONS

In computing the data for tables 1 through 15, the author assumed that the target was at the plotted grid point, and the arrival time of sound generated at shot time (= 0.000 seconds) was computed for each microphone. Then the arrival time at the specified microphone (IP) was incremented by UP milliseconds, and the target location was computed by using the WRAS solution. At the field point the difference between the computed location and the assumed or "true" location is printed (computed - true). In tables 1 through 6 of "error maps," the unit perturbation was assumed to be 1 millisecond. All errors are rounded to the nearest meter. This value was chosen as small enough to produce few errors exceeding 1000 meters, while also producing few errors less than a few meters in at least one of the component directions. The reader is invited to examine the symmetry of error effects between microphones 1 and 6 (tables 1 and 6), 2 and 5 (tables 2 and 5) and 3 and 4 (tables 3 and 4).

The tables show that errors in arrival time at microphones 2 and 5 have relatively small effects at most target points on either component of target location error and that for all microphones the Y-component error is generally several times the X-component error. Further, both microphones 1 and 6 yield large negative Y-component errors for a small positive change in arrival time, while both microphones 3 and 4 yield large positive errors in Y-component for a small positive change in arrival time.

In the above computations and throughout this report, it does not matter whether the "error" in arrival time be the result of an error in reading the acoustic record or the effect of propagation phenomena in causing the signature's apparent arrival time to be different from that which would be expected after correcting for the assumed meteorological conditions. Either cause will result in the same target location error if it

causes the same error in arrival time. For example, at the point $M = -9$, $N = 25$, the upper right-hand + in table 1, one finds that an arrival time error of 1 millisecond ($UP = 1.00$) causes the X-component of target position to be computed to be 18 meters larger than true and the Y-component to be computed to be 49 meters smaller than true (18, -49). For the same point, tables 2 through 6 show that the same unit error, if it occurs at microphones 2 through 6, produces target location errors of (-5, 17), (-14, 40), (-11, 31), (-1, 1), and (13, -41) meters, respectively.

LINEARITY OF ERROR TRANSFER FUNCTIONS

The analysis of the joint effects of several error sources on the overall sound ranging target location error would be much simplified if the output error could be assumed to be linearly dependent upon the input error, or at least approximately so. Tables 2 through 6 show the error fields for input errors of 1 millisecond occurring in microphones 1 through 6, while tables 7 through 12 show the error fields for input errors of 3 milliseconds.

In view of the symmetry noted for errors in microphones 1 and 6, 2 and 5, and 3 and 4, it becomes apparent that the entire story can be told by just the error fields due to microphones 1, 2, and 3. Thus the error fields due to input errors of 10 and 30 milliseconds, shown in tables 13 through 15 and 16 through 18, respectively, are shown only for microphones 1, 2, and 3.

Through most of the error field, output errors in each horizontal component of target location are approximately proportional to input errors. Over a range of 30:1 in input error, proportionality is quite good. The range selected for illustration includes the range of errors to be expected because of normal atmospheric propagation effects and from errors in reading arrival time records.

In assessing the combined effects of several errors affecting the measured arrival time at any microphone, little error will occur if the target location error due to each contributing error is separately computed and the results summed instead of first summing the several contributing errors in arrival time and then computing the target location error which they will cause.

SUPERPOSABILITY OF ERROR TRANSFER FUNCTIONS

The preceding section demonstrated that several simultaneous arrival time errors occurring at a single microphone could be separately transformed into target location errors and then summed to give the aggregate target location error. To investigate the validity of computing errors due to simultaneous arrival time errors in several microphones as the sum of the effects of errors in each microphone, the author assumed errors occurring in one microphone and an additional error occurring in each of the remaining microphones in turn.

In tables 19 through 23, simultaneous errors of 3 milliseconds are assumed to occur in microphone 2 and in microphones 1, 3, 4, 5, and 6 in turn. The reader will be able to readily verify that the effect of the combined simultaneously occurring error is very closely approximated by the sum of the errors given table 8 and tables 7, 9, 10, 11, and 12, respectively.

For example, tables 7 through 12 show that the errors in target location at the point $(M, N) = (-9, 25)$ due to a 3-millisecond error in arrival time at microphones 1 through 6 are (56, -147), (-15, 50), (-42, 120), (-34, 93), (-3, 2), and (40, -124) meters, respectively. For the same target point, table 19 shows that the target location error due to simultaneously occurring 3-millisecond errors in microphones 1 and 2 is (40, -95), almost exactly the sum of the effects of this error acting separately at microphones 1 and 2. The corresponding effect of the combined error in microphones 2 and 3, 2 and 4, 2 and 5, and 2 and 6 are (-58, 172), (-50, 145), (-19, 53) and (15, -74) meters, respectively, as shown in tables 20 through 23. In each case the effect of the simultaneously occurring error is approximately equal to the sum of the effects caused by each error taken as acting alone. Similar results would be found for any selected group of microphones and for any target point.

We have thus shown that the errors in target location resulting from the simultaneous presence of errors in several microphones can be closely approximated by the sum of errors computed as if each error occurred separately in each of the microphones.

CONCLUSIONS

The above analysis has shown that sound ranging solutions obtained by the WRAS solution technique applied to a regular, linear, six-microphone array have the following properties:

1. Errors occurring in arrival time, relative to the assumptions inherent in the solution model, in microphones 1, 3, 4, and 6 have the greatest effect on the solution; while at most field points, microphones 2 and 5 have relatively little effect on the solution.
2. At most field points, the Y-component of target location error due to an error in arrival time at any microphone is generally several times as large as the X-component of error.
3. Positive errors in arrival time at microphones 1 and 6 lead generally to negative Y-component errors, while positive errors in arrival time at microphones 3 and 4 result in positive Y-component errors.
4. Positive errors in arrival time at microphones 1 and 6 lead to positive X-component errors in target locations for left flank targets and negative X-component errors in target locations for right flank targets, while positive errors in arrival time at microphones 3 and 4 lead to positive X-component errors in target location for right flank targets and negative X-component errors in target location for left flank targets.

5. For each horizontal component of target location, the error caused by an error in arrival time at any microphone is approximately proportional to the arrival time error; i.e., the time-to-space error transfer function is approximately linear. Thus the error in target location due to the combined effects of several errors in arrival time at any one microphone is closely approximated by the sum of errors in target location which each of the contributing errors would have caused if acting alone.

6. The error in target location in each component of position resulting from simultaneously occurring errors at two or more microphones is closely approximated by the sum of the errors which each arrival time error would produce if acting alone; i.e., the error contributions are superposable in geometric space.

TABLE 3. X- AND Y-COMPONENT ERRORS DUE TO A 1-MILLISECOND ERROR IN ARRIVAL TIME AT MICROPHONE 3

WEIGHTED RANGE SOLUTION TO EVAL TOT LOCN ERROR AFTER FCMS																			
RL	IP	10	4	8	10	25	1.000	UP	5	1M	0.0	0.00	V1	V2	V3	TE			
0.00	3	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0			
3*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
-9	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0
3*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
-8	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0	-0
3*	6*	-2*	-4*	-5*	-5*	-5*	-5*	-5*	-5*	-5*	-5*	-5*	-5*	-5*	-5*	-5*	-5*	-5*	-5*
-7	-2	0	1	3	4	5	7	8	9	10	12	13	14	16	17	19	20	22	24
3*	19*	2*	-1*	-2*	-3*	-4*	-4*	-4*	-4*	-4*	-4*	-4*	-4*	-4*	-4*	-4*	-4*	-4*	-4*
-6	-5	-1	0	1	3	4	5	7	8	9	10	12	13	14	16	17	19	20	22
3*	16*	3*	0*	-1*	-2*	-3*	-3*	-3*	-3*	-3*	-3*	-3*	-3*	-3*	-3*	-3*	-3*	-3*	-3*
-5	-5	-2	0	1	2	3	5	6	7	8	9	11	12	13	15	16	18	20	21
3*	8*	1*	0*	0*	-1*	-2*	-2*	-2*	-2*	-2*	-2*	-2*	-2*	-2*	-2*	-2*	-2*	-2*	-2*
-4	-4	-2	0	0	2	3	4	5	6	7	8	10	11	12	14	15	17	18	20
3*	1*	0*	0*	0*	-1*	-1*	-1*	-1*	-1*	-1*	-1*	-1*	-1*	-1*	-1*	-1*	-1*	-1*	-1*
-3	-2	-1	0	1	2	3	4	5	6	7	8	9	10	11	13	14	16	18	19
3*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
-2	0	0	0	1	2	3	4	5	6	7	8	9	11	12	14	15	17	19	20
3*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
-1	0	1	1	1	2	2	3	4	5	6	7	8	9	10	11	13	15	16	18
3*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
0	0	0	1	1	1	2	2	3	4	5	6	7	8	9	11	12	14	16	17
3*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
1	0	0	0	0	0	1	2	3	4	5	6	7	8	9	10	12	14	15	17
3*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
2	0	0	0	0	0	0	1	2	3	4	5	6	7	8	9	10	12	13	15
3*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
3	0	0	0	0	0	0	0	1	2	3	4	5	6	7	8	10	11	13	15
3*	-3*	-1*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
-4	-1	-1	-1	-1	-1	0	0	0	1	2	3	4	6	7	8	10	11	13	15
3*	-11*	-3*	-1*	-1*	-1*	0*	0*	0*	1*	1*	1*	2*	3*	4*	5*	6*	7*	8*	9*
5	-3	-2	-1	-1	-1	0	0	0	1	2	3	4	5	7	8	10	11	13	15
3*	-26*	-7*	-3*	-1*	0*	0*	0*	0*	1*	1*	2*	2*	3*	3*	4*	5*	6*	7*	8*
6	-6	-5	-2	-2	-1	0	0	0	1	2	3	4	5	7	8	10	11	13	15
3*	-16*	-12*	-5*	-2*	-1*	0*	0*	0*	1*	1*	2*	2*	3*	4*	5*	6*	7*	8*	9*
7	-9	-5	-3	-2	-1	0	0	0	1	2	3	4	6	7	8	10	12	13	15
3*	-0*	-16*	-7*	-3*	-1*	0*	0*	0*	1*	1*	2*	2*	3*	4*	5*	6*	7*	8*	9*
8	-0	-6	-4	-2	-1	0	0	0	1	2	3	4	6	7	8	10	12	13	15
3*	-0*	-0*	-9*	-4*	-1*	0*	0*	0*	1*	1*	2*	2*	3*	4*	5*	6*	7*	8*	9*
9	-0	-0	-4	-2	-1	0	0	0	1	2	3	4	6	7	8	10	12	13	15

TABLE 5. X- AND Y-COMPONENT ERRORS DUE TO A 1-MILLISECOND ERROR IN ARRIVAL TIME AT MICROPHONE 5

WEIGHTED RANGE SOLUTION TO EVAL TET LOCN ERROR AFTER FCNS										TE									
BL	IP	ID	N	N	PNV	UP	TM	ZZ	V1	V2	V3	V3	V3	V3	V3	V3	V3	V3	V3
4.00	5	8	-9	25	1.000	1.00	5	0.0	0.00	0.00	0.00	0.00	10.00	0.00	10.00	0.00	10.00	0.00	10.00
5*	-0*	-0*	17*	10*	7*	6*	5*	4*	3*	2*	2*	1*	1*	0*	0*	0*	0*	0*	-1*
-9	-0	-0	-7	-6	-5	-5	-4	-4	-4	-4	-4	-3	-3	-2	-2	-1	-1	0	0
5*	-0*	20*	10*	7*	5*	4*	3*	3*	2*	1*	1*	1*	1*	0*	0*	0*	0*	0*	-1*
-8	-0	-6	-5	-4	-4	-4	-4	-4	-3	-3	-3	-3	-3	-2	-2	-1	0	0	1
5*	38*	11*	6*	4*	3*	2*	2*	2*	1*	1*	1*	0*	0*	0*	0*	0*	0*	0*	-1*
-7	-7	-4	-3	-3	-3	-3	-3	-3	-3	-3	-3	-2	-2	-2	-1	0	0	1	2
5*	16*	5*	3*	2*	2*	1*	1*	1*	1*	0*	0*	0*	0*	0*	0*	0*	0*	0*	-1*
-6	-4	-2	-2	-2	-2	-2	-2	-2	-2	-2	-2	-2	-2	-1	-1	0	0	1	2
5*	5*	2*	1*	1*	1*	1*	1*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	-1*
-5	-1	-1	-1	-1	-1	-2	-2	-2	-2	-2	-1	-1	-1	0	0	1	1	2	3
5*	1*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	-1*
-4	0	0	0	-1	-1	-1	-1	-1	-1	-1	-1	0	0	0	0	1	1	2	3
5*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	-1*
-3	0	0	0	0	-1	-1	-1	-1	-1	-1	0	0	0	0	1	2	2	3	4
5*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	-1*
-2	0	0	0	0	-1	-1	-1	0	0	0	0	0	0	1	1	2	3	4	5
5*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
-1	0	0	0	0	0	0	0	0	0	0	0	0	1	1	2	3	4	5	6
5*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
0	0	0	0	0	0	0	0	0	0	1	1	1	2	2	3	4	5	6	7
5*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
1	0	0	0	0	0	0	1	1	1	1	2	2	3	3	4	5	6	7	7
5*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
2	1	2	2	2	2	2	2	2	2	3	3	3	4	4	5	6	7	8	8
5*	4*	2*	2*	1*	1*	1*	1*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
3	3	4	4	4	4	3	3	3	4	4	4	4	5	5	6	7	8	9	9
5*	22*	8*	5*	4*	3*	2*	2*	1*	1*	1*	1*	1*	1*	1*	1*	1*	1*	1*	0*
4	9	7	6	6	5	5	5	5	5	5	5	6	6	6	7	7	8	9	10
5*	68*	71*	12*	8*	6*	5*	4*	3*	3*	2*	2*	2*	2*	1*	1*	1*	1*	1*	1*
5	20	12	10	9	8	7	7	7	7	6	7	7	7	7	7	7	7	7	11
5*	156*	43*	22*	14*	10*	8*	6*	5*	5*	4*	3*	3*	3*	2*	2*	2*	2*	2*	2*
6	34	16	14	12	11	10	9	8	8	8	8	8	8	9	9	10	11	12	13
5*	294*	77*	38*	23*	16*	12*	10*	8*	7*	6*	5*	5*	4*	4*	3*	3*	3*	3*	3*
7	51	27	19	16	14	12	11	10	10	10	10	10	10	11	11	12	13	13	14
5*	-0*	125*	59*	36*	25*	18*	14*	12*	10*	9*	8*	7*	6*	5*	4*	4*	4*	4*	4*
8	-0	36	26	20	16	14	13	13	12	12	12	12	12	13	13	14	14	15	15
5*	-0*	-0*	87*	52*	35*	26*	20*	16*	14*	12*	10*	9*	8*	7*	6*	6*	5*	5*	5*
9	-0	-0	33	26	22	19	17	16	15	15	14	14	14	14	14	15	15	16	17

TABLE 7. X- AND Y-COMPONENT ERRORS DUE TO A 3-MILLISECOND ERROR IN ARRIVAL TIME AT MICROPHONE 1

WEIGHTED RANGE SOLUTION TO EVAL TAT LOCK ERROR AFTER FCMS																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																				
RL	IP	IN	N	UP	IN	22	V1	V2	V3	TE																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																										
4.00	1	8	-9	25	1.000	5.00	5	0.00	0.00	10.00																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																										
1 ⁺ 00000	404 ⁺	203 ⁺	130 ⁺	98 ⁺	76 ⁺	67 ⁺	68 ⁺	52 ⁺	50 ⁺	48 ⁺	48 ⁺	49 ⁺	49 ⁺	50 ⁺	51 ⁺	52 ⁺	53 ⁺	54 ⁺	55 ⁺	56 ⁺																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																
-9	-156	-92	-69	-58	-54	-59	-51	-52	-56	-59	-63	-67	-71	-76	-81	-87	-93	-100	-107	-114	-121	-129	-138	-147																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																												
1 ⁺ 450 ⁺	252 ⁺	130 ⁺	86 ⁺	65 ⁺	55 ⁺	48 ⁺	44 ⁺	40 ⁺	38 ⁺	36 ⁺	34 ⁺	32 ⁺	30 ⁺	28 ⁺	26 ⁺	24 ⁺	22 ⁺	20 ⁺	18 ⁺	16 ⁺	14 ⁺	12 ⁺	10 ⁺	8 ⁺	6 ⁺	4 ⁺	2 ⁺	0 ⁺	-2 ⁺	-4 ⁺	-6 ⁺	-8 ⁺	-10 ⁺	-12 ⁺	-14 ⁺	-16 ⁺	-18 ⁺	-20 ⁺	-22 ⁺	-24 ⁺	-26 ⁺	-28 ⁺	-30 ⁺	-32 ⁺	-34 ⁺	-36 ⁺	-38 ⁺	-40 ⁺	-42 ⁺	-44 ⁺	-46 ⁺	-48 ⁺	-50 ⁺	-52 ⁺	-54 ⁺	-56 ⁺	-58 ⁺	-60 ⁺	-62 ⁺	-64 ⁺	-66 ⁺	-68 ⁺	-70 ⁺	-72 ⁺	-74 ⁺	-76 ⁺	-78 ⁺	-80 ⁺	-82 ⁺	-84 ⁺	-86 ⁺	-88 ⁺	-90 ⁺	-92 ⁺	-94 ⁺	-96 ⁺	-98 ⁺	-100 ⁺	-102 ⁺	-104 ⁺	-106 ⁺	-108 ⁺	-110 ⁺	-112 ⁺	-114 ⁺	-116 ⁺	-118 ⁺	-120 ⁺	-122 ⁺	-124 ⁺	-126 ⁺	-128 ⁺	-130 ⁺	-132 ⁺	-134 ⁺	-136 ⁺	-138 ⁺	-140 ⁺	-142 ⁺	-144 ⁺	-146 ⁺	-148 ⁺	-150 ⁺	-152 ⁺	-154 ⁺	-156 ⁺	-158 ⁺	-160 ⁺	-162 ⁺	-164 ⁺	-166 ⁺	-168 ⁺	-170 ⁺	-172 ⁺	-174 ⁺	-176 ⁺	-178 ⁺	-180 ⁺	-182 ⁺	-184 ⁺	-186 ⁺	-188 ⁺	-190 ⁺	-192 ⁺	-194 ⁺	-196 ⁺	-198 ⁺	-200 ⁺	-202 ⁺	-204 ⁺	-206 ⁺	-208 ⁺	-210 ⁺	-212 ⁺	-214 ⁺	-216 ⁺	-218 ⁺	-220 ⁺	-222 ⁺	-224 ⁺	-226 ⁺	-228 ⁺	-230 ⁺	-232 ⁺	-234 ⁺	-236 ⁺	-238 ⁺	-240 ⁺	-242 ⁺	-244 ⁺	-246 ⁺	-248 ⁺	-250 ⁺	-252 ⁺	-254 ⁺	-256 ⁺	-258 ⁺	-260 ⁺	-262 ⁺	-264 ⁺	-266 ⁺	-268 ⁺	-270 ⁺	-272 ⁺	-274 ⁺	-276 ⁺	-278 ⁺	-280 ⁺	-282 ⁺	-284 ⁺	-286 ⁺	-288 ⁺	-290 ⁺	-292 ⁺	-294 ⁺	-296 ⁺	-298 ⁺	-300 ⁺	-302 ⁺	-304 ⁺	-306 ⁺	-308 ⁺	-310 ⁺	-312 ⁺	-314 ⁺	-316 ⁺	-318 ⁺	-320 ⁺	-322 ⁺	-324 ⁺	-326 ⁺	-328 ⁺	-330 ⁺	-332 ⁺	-334 ⁺	-336 ⁺	-338 ⁺	-340 ⁺	-342 ⁺	-344 ⁺	-346 ⁺	-348 ⁺	-350 ⁺	-352 ⁺	-354 ⁺	-356 ⁺	-358 ⁺	-360 ⁺	-362 ⁺	-364 ⁺	-366 ⁺	-368 ⁺	-370 ⁺	-372 ⁺	-374 ⁺	-376 ⁺	-378 ⁺	-380 ⁺	-382 ⁺	-384 ⁺	-386 ⁺	-388 ⁺	-390 ⁺	-392 ⁺	-394 ⁺	-396 ⁺	-398 ⁺	-400 ⁺	-402 ⁺	-404 ⁺	-406 ⁺	-408 ⁺	-410 ⁺	-412 ⁺	-414 ⁺	-416 ⁺	-418 ⁺	-420 ⁺	-422 ⁺	-424 ⁺	-426 ⁺	-428 ⁺	-430 ⁺	-432 ⁺	-434 ⁺	-436 ⁺	-438 ⁺	-440 ⁺	-442 ⁺	-444 ⁺	-446 ⁺	-448 ⁺	-450 ⁺	-452 ⁺	-454 ⁺	-456 ⁺	-458 ⁺	-460 ⁺	-462 ⁺	-464 ⁺	-466 ⁺	-468 ⁺	-470 ⁺	-472 ⁺	-474 ⁺	-476 ⁺	-478 ⁺	-480 ⁺	-482 ⁺	-484 ⁺	-486 ⁺	-488 ⁺	-490 ⁺	-492 ⁺	-494 ⁺	-496 ⁺	-498 ⁺	-500 ⁺	-502 ⁺	-504 ⁺	-506 ⁺	-508 ⁺	-510 ⁺	-512 ⁺	-514 ⁺	-516 ⁺	-518 ⁺	-520 ⁺	-522 ⁺	-524 ⁺	-526 ⁺	-528 ⁺	-530 ⁺	-532 ⁺	-534 ⁺	-536 ⁺	-538 ⁺	-540 ⁺	-542 ⁺	-544 ⁺	-546 ⁺	-548 ⁺	-550 ⁺	-552 ⁺	-554 ⁺	-556 ⁺	-558 ⁺	-560 ⁺	-562 ⁺	-564 ⁺	-566 ⁺	-568 ⁺	-570 ⁺	-572 ⁺	-574 ⁺	-576 ⁺	-578 ⁺	-580 ⁺	-582 ⁺	-584 ⁺	-586 ⁺	-588 ⁺	-590 ⁺	-592 ⁺	-594 ⁺	-596 ⁺	-598 ⁺	-600 ⁺	-602 ⁺	-604 ⁺	-606 ⁺	-608 ⁺	-610 ⁺	-612 ⁺	-614 ⁺	-616 ⁺	-618 ⁺	-620 ⁺	-622 ⁺	-624 ⁺	-626 ⁺	-628 ⁺	-630 ⁺	-632 ⁺	-634 ⁺	-636 ⁺	-638 ⁺	-640 ⁺	-642 ⁺	-644 ⁺	-646 ⁺	-648 ⁺	-650 ⁺	-652 ⁺	-654 ⁺	-656 ⁺	-658 ⁺	-660 ⁺	-662 ⁺	-664 ⁺	-666 ⁺	-668 ⁺	-670 ⁺	-672 ⁺	-674 ⁺	-676 ⁺	-678 ⁺	-680 ⁺	-682 ⁺	-684 ⁺	-686 ⁺	-688 ⁺	-690 ⁺	-692 ⁺	-694 ⁺	-696 ⁺	-698 ⁺	-700 ⁺	-702 ⁺	-704 ⁺	-706 ⁺	-708 ⁺	-710 ⁺	-712 ⁺	-714 ⁺	-716 ⁺	-718 ⁺	-720 ⁺	-722 ⁺	-724 ⁺	-726 ⁺	-728 ⁺	-730 ⁺	-732 ⁺	-734 ⁺	-736 ⁺	-738 ⁺	-740 ⁺	-742 ⁺	-744 ⁺	-746 ⁺	-748 ⁺	-750 ⁺	-752 ⁺	-754 ⁺	-756 ⁺	-758 ⁺	-760 ⁺	-762 ⁺	-764 ⁺	-766 ⁺	-768 ⁺	-770 ⁺	-772 ⁺	-774 ⁺	-776 ⁺	-778 ⁺	-780 ⁺	-782 ⁺	-784 ⁺	-786 ⁺	-788 ⁺	-790 ⁺	-792 ⁺	-794 ⁺	-796 ⁺	-798 ⁺	-800 ⁺	-802 ⁺	-804 ⁺	-806 ⁺	-808 ⁺	-810 ⁺	-812 ⁺	-814 ⁺	-816 ⁺	-818 ⁺	-820 ⁺	-822 ⁺	-824 ⁺	-826 ⁺	-828 ⁺	-830 ⁺	-832 ⁺	-834 ⁺	-836 ⁺	-838 ⁺	-840 ⁺	-842 ⁺	-844 ⁺	-846 ⁺	-848 ⁺	-850 ⁺	-852 ⁺	-854 ⁺	-856 ⁺	-858 ⁺	-860 ⁺	-862 ⁺	-864 ⁺	-866 ⁺	-868 ⁺	-870 ⁺	-872 ⁺	-874 ⁺	-876 ⁺	-878 ⁺	-880 ⁺	-882 ⁺	-884 ⁺	-886 ⁺	-888 ⁺	-890 ⁺	-892 ⁺	-894 ⁺	-896 ⁺	-898 ⁺	-900 ⁺	-902 ⁺	-904 ⁺	-906 ⁺	-908 ⁺	-910 ⁺	-912 ⁺	-914 ⁺	-916 ⁺	-918 ⁺	-920 ⁺	-922 ⁺	-924 ⁺	-926 ⁺	-928 ⁺	-930 ⁺	-932 ⁺	-934 ⁺	-936 ⁺	-938 ⁺	-940 ⁺	-942 ⁺	-944 ⁺	-946 ⁺	-948 ⁺	-950 ⁺	-952 ⁺	-954 ⁺	-956 ⁺	-958 ⁺	-960 ⁺	-962 ⁺	-964 ⁺	-966 ⁺	-968 ⁺	-970 ⁺	-972 ⁺	-974 ⁺	-976 ⁺	-978 ⁺	-980 ⁺	-982 ⁺	-984 ⁺	-986 ⁺	-988 ⁺	-990 ⁺	-992 ⁺	-994 ⁺	-996 ⁺	-998 ⁺	-1000 ⁺	-1002 ⁺	-1004 ⁺	-1006 ⁺	-1008 ⁺	-1010 ⁺	-1012 ⁺	-1014 ⁺	-1016 ⁺	-1018 ⁺	-1020 ⁺	-1022 ⁺	-1024 ⁺	-1026 ⁺	-1028 ⁺	-1030 ⁺	-1032 ⁺	-1034 ⁺	-1036 ⁺	-1038 ⁺	-1040 ⁺	-1042 ⁺	-1044 ⁺	-1046 ⁺	-1048 ⁺	-1050 ⁺	-1052 ⁺	-1054 ⁺	-1056 ⁺	-1058 ⁺	-1060 ⁺	-1062 ⁺	-1064 ⁺	-1066 ⁺	-1068 ⁺	-1070 ⁺	-1072 ⁺	-1074 ⁺	-1076 ⁺	-1078 ⁺	-1080 ⁺	-1082 ⁺	-1084 ⁺	-1086 ⁺	-1088 ⁺	-1090 ⁺	-1092 ⁺	-1094 ⁺	-1096 ⁺	-1098 ⁺	-1100 ⁺	-1102 ⁺	-1104 ⁺	-1106 ⁺	-1108 ⁺	-1110 ⁺	-1112 ⁺	-1114 ⁺	-1116 ⁺	-1118 ⁺	-1120 ⁺	-1122 ⁺	-1124 ⁺	-1126 ⁺	-1128 ⁺	-1130 ⁺	-1132 ⁺	-1134 ⁺	-1136 ⁺	-1138 ⁺	-1140 ⁺	-1142 ⁺	-1144 ⁺	-1146 ⁺	-1148 ⁺	-1150 ⁺	-1152 ⁺	-1154 ⁺	-1156 ⁺	-1158 ⁺	-1160 ⁺	-1162 ⁺	-1164 ⁺	-1166 ⁺	-1168 ⁺	-1170 ⁺	-1172 ⁺	-1174 ⁺	-1176 ⁺	-1178 ⁺	-1180 ⁺	-1182 ⁺	-1184 ⁺	-1186 ⁺	-1188 ⁺	-1190 ⁺	-1192 ⁺	-1194 ⁺	-1196 ⁺	-1198 ⁺	-1200 ⁺	-1202 ⁺	-1204 ⁺	-1206 ⁺	-1208 ⁺	-1210 ⁺	-1212 ⁺	-1214 ⁺	-1216 ⁺	-1218 ⁺	-1220 ⁺	-1222 ⁺	-1224 ⁺	-1226 ⁺	-1228 ⁺	-1230 ⁺	-1232 ⁺	-1234 ⁺	-1236 ⁺	-1238 ⁺	-1240 ⁺	-1242 ⁺	-1244 ⁺	-1246 ⁺	-1248 ⁺	-1250 ⁺	-1252 ⁺	-1254 ⁺	-1256 ⁺	-1258 ⁺	-1260 ⁺	-1262 ⁺	-1264 ⁺	-1266 ⁺	-1268 ⁺	-1270 ⁺	-1272 ⁺	-1274 ⁺	-1276 ⁺	-1278 ⁺	-1280 ⁺	-1282 ⁺	-1284 ⁺	-1286 ⁺	-1288 ⁺	-1290 ⁺	-1292 ⁺	-1294 ⁺	-1296 ⁺	-1298 ⁺	-1300 ⁺	-1302 ⁺	-1304 ⁺	-1306 ⁺	-1308 ⁺	-1310 ⁺	-1312 ⁺	-1314 ⁺	-1316 ⁺	-1318 ⁺	-1320 ⁺	-1322 ⁺	-1324 ⁺	-1326 ⁺	-1328 ⁺	-1330 ⁺	-1332 ⁺	-1334 ⁺	-1336 ⁺	-1338 ⁺	-1340 ⁺	-1342 ⁺	-1344 ⁺	-1346 ⁺	-1348 ⁺	-1350 ⁺	-1352 ⁺	-1354 ⁺	-1356 ⁺	-1358 ⁺	-1360 ⁺	-1362 ⁺	-1364 ⁺	-1366 ⁺	-1368 ⁺	-1370 ⁺	-1372 ⁺	-1374 ⁺	-1376 ⁺	-1378 ⁺	-1380 ⁺	-1382 ⁺	-1384 ⁺	-1386 ⁺	-1388 ⁺	-1390 ⁺	-1392 ⁺	-1394 ⁺	-1396 ⁺	-1398 ⁺	-1400 ⁺	-1402 ⁺	-1404 ⁺	-1406 ⁺	-1408 ⁺	-1410 ⁺	-1412 ⁺	-1414 ⁺	-1416 ⁺	-1418 ⁺	-1420 ⁺	-1422 ⁺	-1424 ⁺	-1426 ⁺	-1428 ⁺	-1430 ⁺	-1432 ⁺	-1434 ⁺	-1436 ⁺	-1438 ⁺	-1440 ⁺	-1442 ⁺	-1444 ⁺	-1446 ⁺	-1448 ⁺	-1450 ⁺	-1452 ⁺	-1454 ⁺	-1456 ⁺	-1458 ⁺	-1460 ⁺	-1462 ⁺	-1464 ⁺	-1466 ⁺	-1468 ⁺	-1470 ⁺	-1472 ⁺	-1474 ⁺	-1476 ⁺	-1478 ⁺	-1480 ⁺	-1482 ⁺	-1484 ⁺	-1486 ⁺	-1488 ⁺	-1490 ⁺	-1492 ⁺	-1494 ⁺	-1496 ⁺	-1498 ⁺	-1500 ⁺	-1502 ⁺	-1504 ⁺	-1506 ⁺	-1508 ⁺	-1510 ⁺	-1512 ⁺	-1514 ⁺	-1516 ⁺	-1518 ⁺	-1520 ⁺	-1522 ⁺	-1524 ⁺	-1526 ⁺	-1528 ⁺	-1530 ⁺	-1532 ⁺	-1534 ⁺	-1536 ⁺	-1538 ⁺	-1540 ⁺	-1542 ⁺	-1544 ⁺	-1546 ⁺	-1548 ⁺	-1550 ⁺	-1552 ⁺	-1554 ⁺	-1556 ⁺	-1558 ⁺	-1560 ⁺	-1562 ⁺	-1564 ⁺	-1566 ⁺	-1568 ⁺	-1570 ⁺	-1572 ⁺	-1574 ⁺	-1576 ⁺	-1578 ⁺	-1580 ⁺	-1582 ⁺	-1584 ⁺	-1586 ⁺	-1588 ⁺	-1590 ⁺	-1592 ⁺	-1594 ⁺	-1596 ⁺	-1598 ⁺	-1600 ⁺	-1602 ⁺	-1604 ⁺	-1606 ⁺	-1608 ⁺	-1610 ⁺	-1612 ⁺	-1614 ⁺	-1616 ⁺	-1618 ⁺	-1620 ⁺	-1622 ⁺	-1624 ⁺	-1626 ⁺	-1628 ⁺	-1630 ⁺	-1632 ⁺	-1634 ⁺	-1636 ⁺	-1638 ⁺	-1640 ⁺	-1642 ⁺	-1644 ⁺	-1646 ⁺	-1648 ⁺	-1650 ⁺	-1652 ⁺	-1654 ⁺	-1656 ⁺	-1658 ⁺	-1660 ⁺	-1662 ⁺	-1664 ⁺	-1666 ⁺	-1668 ⁺	-1670 ⁺	-1672 ⁺	-1674 ⁺	-1676 ⁺	-1678 ⁺	-1680

TABLE 9. X- AND Y-COMPONENT ERRORS DUE TO A 3-MILLISECOND ERROR IN ARRIVAL TIME AT MICROPHONE 3

WEIGHTED RANGE SOLUTION TO EVAL TAT LVEN ZERRR AFTER PCMS																			
RL	IP	1A	M	N	Q	UP	TM	2Z	V1	V2	V3	VE							
4.00	3	8	9	25	1.000	3.00	5	0.0	0.00	0.00	0.00	10.00							
3*-100	-101	-67	-32	-88	-80	-30	-17	-30	-35	-35	-35	-35	-37	-38	-39	-40	-41	-42	-43
-9	11	23	23	24	24	31	34	36	41	45	49	53	57	62	66	71	76	82	88
3*-27	-42	-33	-29	-28	-27	-27	-27	-27	-27	-28	-28	-28	-28	-29	-30	-31	-32	-33	-34
-8	-2	9	12	15	18	22	25	29	32	36	40	44	48	52	57	61	66	71	77
3* 43	-64	-13	-16	-17	-18	-19	-20	-20	-21	-21	-22	-22	-22	-23	-23	-24	-25	-26	-27
-7	-12	0	5	9	13	17	21	24	28	32	35	39	43	48	52	57	62	67	72
3* 64	74	-3	-8	-10	-12	-14	-16	-18	-20	-22	-24	-26	-28	-30	-32	-34	-36	-38	-40
-6	-18	-5	0	5	9	13	17	21	25	28	32	36	40	44	48	53	58	63	68
3* 50	9	0	-4	-7	-8	-9	-10	-11	-12	-13	-14	-15	-16	-17	-18	-19	-20	-21	-22
-5	-17	-7	-1	3	7	11	15	18	22	25	29	32	36	40	45	49	54	59	64
3* 24	5	0	-2	-4	-6	-8	-10	-12	-14	-16	-18	-20	-22	-24	-26	-28	-30	-32	-34
-4	-12	-6	-2	2	6	10	13	16	20	23	26	30	34	38	42	46	51	56	61
3* 54	14	0	-2	-3	-4	-5	-6	-7	-8	-9	-10	-11	-12	-13	-14	-15	-16	-17	-18
-3	-6	-4	-1	2	6	9	12	15	18	21	24	27	31	35	39	44	49	54	59
3* 0	0	0	-1	-2	-3	-4	-5	-6	-7	-8	-9	-10	-11	-12	-13	-14	-15	-16	-17
-2	-2	1	4	7	9	11	14	16	19	22	25	29	33	37	42	46	51	56	61
3* -1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
-1	1	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
3* 1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19
3* 0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
1	-1	-1	0	0	2	4	6	9	11	14	17	20	24	28	32	37	41	46	51
3* 0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
2	0	-1	-1	0	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14
3* -1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
3	-1	-2	-2	-1	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14
3* -9	-3	-2	-1	0	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14
4	-4	-4	-4	-3	-2	-1	0	1	2	3	4	5	6	7	8	9	10	11	12
3* -33	-10	-5	-3	-1	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14
5	-11	-7	-5	-4	-3	-2	-1	0	1	2	3	4	5	6	7	8	9	10	11
3* -80	-22	-10	-5	-3	-1	0	1	2	3	4	5	6	7	8	9	10	11	12	13
6	-20	-11	-8	-6	-4	-3	-2	-1	0	1	2	3	4	5	6	7	8	9	10
3* -151	-37	-16	-8	-4	-2	-1	0	1	2	3	4	5	6	7	8	9	10	11	12
7	-30	-15	-10	-7	-4	-2	-1	0	1	2	3	4	5	6	7	8	9	10	11
3* -245	-56	-23	-11	-6	-3	-1	0	1	2	3	4	5	6	7	8	9	10	11	12
8	-41	-19	-12	-8	-5	-3	-1	0	1	2	3	4	5	6	7	8	9	10	11
3* -165	-74	-28	-12	-6	-3	-1	0	1	2	3	4	5	6	7	8	9	10	11	12
9	-53	-22	-13	-8	-5	-3	-1	0	1	2	3	4	5	6	7	8	9	10	11

TABLE 10. X- AND Y-COMPONENT ERRORS DUE TO A 3-MILLISECOND ERROR IN ARRIVAL TIME AT MICROPHONE 4

WEIGHTED RANGE SOLUTION TO EVAL TAT LOCN ERROR XFER FCMS																									
RL	IP	M	N	OV	UP	1W	ZZ	V1	V2	V3	TE														
4.00	4	8	9	25	1.000	3.00	5	0.0	0.00	0.00	10.00														
4*	365*	78*	28*	12*	4*	0*	-4*	-7*	-9*	-11*	-13*	-15*	-17*	-19*	-20*	-22*	-23*	-25*	-26*	-27*	-29*	-30*	-31*	-33*	-34*
-9	-33	-22	-13	-8	-4	-1	1	5	8	12	16	20	24	28	33	38	43	49	54	60	66	73	79	86	93
4*	245*	56*	23*	11*	4*	0*	-2*	-5*	-7*	-9*	-11*	-13*	-15*	-17*	-18*	-20*	-21*	-22*	-24*	-25*	-26*	-27*	-28*	-30*	
-8	-41	-19	-12	-6	-5	-5	0	4	7	11	14	18	23	27	32	36	42	47	53	58	64	71	77	84	92
4*	151*	37*	16*	8*	3*	0*	-2*	-4*	-6*	-7*	-9*	-11*	-13*	-14*	-16*	-17*	-18*	-19*	-20*	-21*	-22*	-23*	-24*	-26*	
-7	-30	-15	-10	-7	-4	-2	0	3	6	10	14	18	22	26	31	35	40	46	51	57	63	70	76	83	90
4*	80*	22*	10*	5*	2*	0*	-1*	-3*	-5*	-8*	-9*	-10*	-11*	-12*	-13*	-14*	-15*	-16*	-17*	-18*	-19*	-20*	-21*	-22*	
-6	-20	-11	-6	-4	-1	0	3	6	10	13	17	21	25	30	35	40	45	50	56	62	69	75	82	89	
4*	33*	10*	5*	3*	1*	0*	-1*	-3*	-4*	-5*	-6*	-7*	-8*	-9*	-10*	-11*	-12*	-13*	-14*	-15*	-16*	-17*	-18*	-19*	
-5	-11	-7	-5	-4	-3	-1	1	4	7	10	13	17	21	25	30	34	39	45	50	56	62	68	75	81	88
4*	9*	3*	2*	1*	0*	0*	-1*	-2*	-3*	-4*	-5*	-6*	-7*	-8*	-9*	-10*	-11*	-12*	-13*	-14*	-15*	-16*	-17*	-18*	
-4	-4	-1	-4	-3	-2	0	2	4	7	11	14	18	21	26	30	35	39	45	50	56	62	68	74	81	88
4*	1*	0*	0*	0*	0*	-1*	-1*	-2*	-3*	-4*	-5*	-6*	-7*	-8*	-9*	-10*	-11*	-12*	-13*	-14*	-15*	-16*	-17*	-18*	
-3	-1	-2	-2	-1	0	3	5	8	11	15	18	22	26	30	35	40	45	50	56	62	68	75	81	88	
4*	0*	0*	0*	0*	0*	-1*	-1*	-2*	-2*	-3*	-3*	-4*	-4*	-5*	-5*	-6*	-6*	-7*	-7*	-8*	-8*	-9*	-9*	-10*	
-2	0	-1	-1	-1	0	2	4	7	10	13	16	19	23	27	31	36	40	46	51	56	62	69	75	82	89
4*	0*	0*	0*	0*	0*	-1*	-1*	-1*	-1*	-1*	-1*	-2*	-2*	-2*	-2*	-3*	-3*	-3*	-3*	-3*	-3*	-3*	-4*	-4*	
-1	-1	-1	0	0	2	4	6	9	11	14	17	20	24	28	32	37	41	46	52	57	63	69	76	83	90
4*	-1*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	
0	1	2	3	4	5	6	8	10	13	16	19	22	26	29	34	38	43	48	53	59	65	71	77	84	91
4*	1*	0*	0*	0*	0*	0*	1*	1*	1*	1*	1*	1*	1*	1*	1*	1*	1*	1*	1*	1*	1*	1*	1*	1*	
1	1	3	4	5	6	8	10	12	15	17	20	24	27	31	35	40	44	49	55	60	66	72	79	86	93
4*	0*	0*	0*	1*	2*	2*	2*	2*	3*	3*	3*	3*	3*	4*	4*	4*	5*	5*	5*	5*	5*	6*	6*	6*	
2	-2	-2	1	4	7	0	11	14	16	19	22	25	29	33	37	42	46	51	57	62	68	74	81	88	95
4*	-3*	-1*	0*	2*	3*	4*	4*	5*	5*	5*	5*	6*	6*	6*	7*	7*	7*	8*	8*	8*	9*	9*	10*	10*	
3	-6	-4	-1	2	6	0	12	15	18	21	24	27	31	35	39	44	49	54	59	65	71	77	83	90	97
4*	-2*	-1*	0*	2*	4*	4*	6*	7*	8*	8*	8*	9*	9*	10*	10*	10*	11*	11*	12*	12*	13*	13*	14*	15*	
4	-12	-6	-2	6	10	13	16	20	23	26	30	34	38	42	46	51	56	62	67	73	79	86	93	100	
4*	-50*	-9*	0*	4*	7*	8*	9*	10*	11*	11*	12*	12*	13*	13*	14*	14*	15*	15*	16*	16*	17*	17*	18*	19*	
5	-17	-7	-1	3	7	11	15	18	22	25	29	32	36	40	45	49	54	59	65	70	76	83	89	96	103
4*	-6*	-7*	3*	8*	10*	12*	14*	14*	15*	16*	16*	17*	17*	18*	18*	19*	20*	20*	21*	22*	22*	23*	23*	24*	
6	-18	-5	0	5	9	13	17	21	25	28	32	36	40	44	48	53	58	63	68	74	80	86	93	100	
4*	-43*	6*	13*	16*	17*	18*	19*	20*	20*	21*	21*	22*	22*	23*	23*	24*	24*	25*	25*	26*	27*	27*	28*	29*	
7	-12	0	5	9	13	17	21	24	28	32	35	39	43	48	52	57	62	67	72	78	84	90	97	104	111
4*	27*	42*	33*	29*	28*	27*	27*	27*	27*	27*	28*	28*	28*	28*	29*	29*	30*	30*	31*	32*	32*	33*	34*	35*	
8	-2	9	12	15	19	22	25	29	32	36	40	44	48	52	57	61	66	71	77	83	89	95	101	108	115
4*	185*	105*	67*	52*	44*	40*	38*	37*	36*	35*	35*	35*	35*	35*	36*	36*	36*	37*	37*	38*	38*	39*	40*	41*	42*
9	11	23	23	24	25	26	31	34	38	41	45	49	53	57	62	66	71	76	82	88	94	100	106	113	120

TABLE 11. X- AND Y-COMPONENT ERRORS DUE TO A 3-MILLISECOND ERROR IN ARRIVAL TIME AT MICROPHONE 5

WEIGHTED RANGE SOLUTION TO EVAL Y&Y LOC ERROR XPER FCMS																			
BL	IP	1A	M	N	XY	UP	TM	ZZ	V1	V2	V3	Tc							
4.00	5	8	-9	25	1.000	3.00	5	0.0	0.00	0.00	0.00	10.00							
5* 415*	106*	51*	32*	23*	18*	15*	13*	11*	9*	8*	7*	5*	4*	3*	2*	1*	0*	0*	0*
-9 -57	-29	-21	-18	-16	-14	-13	-12	-11	-10	-9	-8	-7	-6	-5	-4	-3	-2	-1	0
5* 233*	62*	32*	21*	16*	13*	11*	9*	8*	7*	5*	4*	3*	2*	1*	0*	0*	0*	0*	0*
-8 -38	-20	-15	-13	-12	-12	-12	-12	-12	-11	-11	-10	-9	-8	-7	-6	-5	-4	-3	-2
5* 117*	33*	18*	12*	10*	8*	7*	6*	5*	4*	4*	3*	2*	1*	0*	0*	0*	0*	0*	0*
-7 -23	-13	-10	-10	-9	-10	-10	-10	-10	-9	-9	-8	-7	-6	-5	-4	-3	-2	-1	0
5* 50*	15*	9*	7*	6*	5*	4*	3*	3*	3*	2*	2*	1*	0*	0*	0*	0*	0*	0*	0*
-6 -12	-7	-6	-7	-7	-8	-8	-8	-8	-8	-8	-7	-6	-5	-4	-3	-2	-1	0	1
5* 16*	6*	4*	3*	3*	3*	3*	2*	2*	1*	1*	0*	0*	0*	0*	0*	0*	0*	0*	0*
-5 -5	-4	-4	-4	-5	-6	-6	-7	-7	-6	-6	-5	-4	-3	-2	-1	0	0	2	3
5* 3*	1*	1*	1*	2*	1*	1*	1*	1*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
-4 -1	-1	-2	-3	-4	-5	-5	-5	-5	-4	-4	-3	-2	-1	0	1	2	3	5	6
5* 0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
-3 0	0	-1	-2	-3	-4	-4	-4	-4	-3	-3	-2	-1	0	1	2	3	4	5	7
5* 0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
-2 0	0	-1	-2	-3	-3	-3	-2	-2	-1	-1	0	0	1	2	3	4	5	6	8
5* 0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
-1 0	0	-1	-2	-2	-2	-1	-1	0	0	0	1	2	3	4	5	6	7	9	10
5* 0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
0 -1	-1	0	0	0	0	0	1	1	2	3	4	5	6	7	8	10	11	12	14
5* -1*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
1 1	1	2	2	2	2	3	3	4	5	5	6	7	8	9	10	11	12	14	15
5* 1*	1*	1*	1*	1*	1*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*	0*
2 3	7	8	7	7	7	7	7	7	8	8	9	10	11	12	13	14	15	16	18
5* 12*	8*	7*	5*	4*	3*	3*	2*	2*	2*	2*	1*	1*	1*	1*	1*	1*	1*	1*	1*
3 10	12	13	13	12	11	11	11	11	12	12	13	13	14	15	16	17	18	20	21
5* 67*	26*	17*	13*	10*	8*	7*	6*	5*	4*	4*	4*	3*	3*	3*	3*	3*	3*	3*	3*
4 29	21	20	19	18	17	16	16	16	16	16	16	17	18	19	20	21	22	23	24
5* 912*	64*	36*	25*	19*	15*	12*	10*	9*	8*	7*	6*	6*	5*	5*	5*	5*	5*	5*	5*
5 61	36	30	27	25	23	22	21	21	20	20	20	21	22	23	24	25	26	28	29
5* 489*	132*	68*	44*	32*	24*	17*	14*	13*	11*	10*	10*	9*	8*	8*	8*	7*	7*	7*	7*
6 106	57	43	37	33	30	28	27	26	26	25	25	26	26	27	28	29	30	32	33
5* 922*	236*	114*	71*	50*	34*	25*	22*	19*	17*	15*	14*	13*	12*	11*	11*	10*	10*	9*	9*
7 161	82	59	48	42	34	26	22	20	18	16	15	14	13	12	11	10	9	8	8
5* 350*	179*	108*	75*	54*	44*	36*	31*	27*	23*	21*	19*	18*	17*	16*	15*	14*	13*	12*	12*
8 220	111	78	62	53	44	44	41	39	37	36	36	36	37	37	38	39	40	41	42
5* 588*	263*	156*	106*	74*	61*	50*	42*	36*	32*	28*	26*	24*	22*	20*	19*	18*	17*	16*	15*
9 270	144	99	78	66	54	53	49	47	45	43	42	41	41	42	43	44	45	46	47

TABLE 12. X- AND Y-COMPONENT ERRORS DUE TO A 3-MILLISECOND ERROR IN ARRIVAL TIME AT MICROPHONE 6

WEIGHTED RANGE SOLUTION TO EVAL T ₀ T LOCN ERROR XFER FCNS											
RL	IP	1 ^h	M	N	UP	TM	ZZ	V1	V2	V3	TE
4.00	6	8	-9	25	1.000	3.00	5	0.00	0.00	0.00	10.00
6 ⁺ 139 ⁺	9 ⁺	48 ⁺	33 ⁺	24 ⁺	21 ⁺	22 ⁺	22 ⁺	23 ⁺	24 ⁺	25 ⁺	26 ⁺
-9 -46	-25	-19	-18	-18	-10	-20	-23	-26	-29	-33	-37
6 ⁺ 171 ⁺	48 ⁺	26 ⁺	19 ⁺	16 ⁺	15 ⁺	15 ⁺	17 ⁺	18 ⁺	19 ⁺	20 ⁺	21 ⁺
-8 -27	-15	-12	-12	-13	-14	-16	-19	-22	-25	-29	-33
6 ⁺ 76 ⁺	21 ⁺	13 ⁺	10 ⁺	10 ⁺	10 ⁺	11 ⁺	12 ⁺	13 ⁺	14 ⁺	15 ⁺	17 ⁺
-7 -14	-8	-7	-8	-9	-11	-13	-16	-19	-22	-26	-30
6 ⁺ 28 ⁺	9 ⁺	6 ⁺	5 ⁺	5 ⁺	6 ⁺	7 ⁺	8 ⁺	9 ⁺	10 ⁺	11 ⁺	12 ⁺
-6 -7	-4	-5	-6	-6	-8	-10	-13	-16	-20	-24	-28
6 ⁺ 8 ⁺	3 ⁺	2 ⁺	2 ⁺	3 ⁺	4 ⁺	5 ⁺	6 ⁺	7 ⁺	8 ⁺	9 ⁺	10 ⁺
-5 -2	-2	-2	-3	-4	-6	-9	-11	-15	-18	-22	-26
6 ⁺ 1 ⁺	0 ⁺	0 ⁺	1 ⁺	1 ⁺	2 ⁺	3 ⁺	4 ⁺	5 ⁺	6 ⁺	7 ⁺	8 ⁺
-4 0	0	-1	-2	-3	-5	-8	-10	-14	-17	-21	-25
6 ⁺ 0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺
-3 0	0	0	-1	-3	-5	-7	-10	-13	-16	-20	-25
6 ⁺ 0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺
-2 0	0	0	-1	-3	-5	-7	-10	-13	-16	-20	-24
6 ⁺ 0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺
-1 0	0	0	-2	-3	-5	-8	-10	-14	-17	-21	-25
6 ⁺ 0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺
0 0	0	0	-1	-3	-5	-8	-10	-13	-16	-20	-24
6 ⁺ 0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺	0 ⁺
1 -1	-2	-3	-4	-6	-9	-10	-13	-16	-20	-24	-28
6 ⁺ -1 ⁺	-3	-5	-6	-8	-10	-12	-15	-18	-22	-26	-30
2 -1	-3	-5	-6	-8	-10	-12	-15	-18	-22	-26	-30
6 ⁺ -4 ⁺	-8	-10	-12	-15	-18	-22	-26	-30	-34	-38	-42
3 -2	-4	-7	-9	-11	-13	-15	-18	-21	-24	-28	-32
6 ⁺ -26 ⁺	-13 ⁺	-11 ⁺	-10 ⁺	-11 ⁺	-11 ⁺	-11 ⁺	-11 ⁺	-12 ⁺	-13 ⁺	-14 ⁺	-15 ⁺
4 -8	-4	-10	-12	-14	-16	-18	-21	-24	-27	-31	-35
6 ⁺ -93 ⁺	-34 ⁺	-23 ⁺	-19 ⁺	-17 ⁺	-16 ⁺	-16 ⁺	-16 ⁺	-17 ⁺	-18 ⁺	-19 ⁺	-20 ⁺
5 -21	-15	-16	-16	-19	-20	-22	-25	-28	-31	-35	-39
6 ⁺ -135 ⁺	-75 ⁺	-44 ⁺	-33 ⁺	-29 ⁺	-24 ⁺	-20 ⁺	-23 ⁺	-26 ⁺	-29 ⁺	-33 ⁺	-37 ⁺
6 -43	-27	-24	-23	-24	-26	-28	-30	-33	-36	-40	-44
6 ⁺ -101 ⁺	-145 ⁺	-78 ⁺	-55 ⁺	-44 ⁺	-38 ⁺	-34 ⁺	-32 ⁺	-31 ⁺	-30 ⁺	-30 ⁺	-30 ⁺
7 -73	-44	-35	-32	-32	-32	-34	-36	-39	-42	-45	-49
6 ⁺ -50 ⁺	-252 ⁺	-130 ⁺	-86 ⁺	-66 ⁺	-55 ⁺	-48 ⁺	-44 ⁺	-42 ⁺	-40 ⁺	-39 ⁺	-39 ⁺
6 -111	-65	-50	-44	-42	-41	-42	-43	-46	-48	-50	-54
6 ⁺ -401 ⁺	-203 ⁺	-130 ⁺	-96 ⁺	-78 ⁺	-67 ⁺	-60 ⁺	-55 ⁺	-52 ⁺	-50 ⁺	-48 ⁺	-48 ⁺
9 -156	-69	-58	-54	-54	-55	-51	-42	-34	-26	-19	-12

REFERENCES

1. Swingle, Donald M., Craig M. Crenshaw, and Raymond Bellucci, 1972, "Improved Sound Ranging Location of Enemy Artillery," Army Science Conference, US Military Academy, West Point, NJ.
2. Swingle, Donald M., and Raymond Bellucci, 1973, "Improved Sound Ranging Location of Enemy Artillery," R&D Technical Report ECOM-5486, US Army Electronics Command, Fort Monmouth, NJ.
3. Personal communications between Dr. Craig M. Crenshaw and Dr. Donald M. Swingle, June 1972-December 1973.
4. Crenshaw, Craig M., 1972, "Sound Ranging Calculations," AMC Chief Scientist Technical Note Number 1, US Army Materiel Command, Alexandria, VA.
5. Arnold, A., and R. Bellucci, 1957, "Variability of Ballistic Meteorological Parameters," Technical Memorandum M-1913, US Army Signal Engineering Laboratories, Fort Monmouth, NJ.
6. Lowenthal, Marvin J., and Raymond Bellucci, 1970, "Variability of Ballistic Winds, R&D Technical Report ECOM-3259, US Army Electronics Command, Fort Monmouth, NJ.
7. Fox, H. L., 1968, "Meteorological Techniques for Sound Ranging; Theory of Errors," Technical Report ECOM-0233-2, US Army Electronics Command, Fort Monmouth, NJ.
8. Lee, Robert P., 1972, "Artillery Sound Ranging Computer Simulations," R&D Technical Report ECOM-5441, US Army Electronics Command, White Sands Missile Range, NM.
9. Bellucci, Raymond, 1966, "Studies of Meteorological Techniques for Sound Ranging: Report II, Error Analysis," Technical Report ECOM-2703, US Army Electronics Command, Fort Monmouth, NJ.
10. Personal communications between Raymond Bellucci and Dr. Donald M. Swingle, June 1966-June 1972.

APPENDIX

THE WEIGHTED RANGE EQUATION SOLUTION

Given microphone positions $(x, y, z)_i$, arrival time t_i , target position (X, Y, Z) , shot time T , effective mean air velocity components $(u, v, w)_i$ and sound speed c_i , we can write the equation connecting these as follows:

$$\begin{aligned} & \left[(X - x_i) + u_i(t_i - T) \right]^2 + \left[(Y - y_i) + v_i(t_i - T) \right]^2 \\ & + \left[(Z - z_i) + w_i(t_i - T) \right]^2 - c_i^2(t_i - T)^2 = e_i. \end{aligned} \quad (A1)$$

With real data, there may be errors in our determination of any of the subscripted variables in the left-hand member, so that the e_i are generally nonzero. Expansion and rearrangement yield

$$R_i^2 - P_i^2 = e_i, \quad (A2)$$

where, denoting the effective speed of sound travel toward each microphone by s_i ,

$$R_i^2 = (X - x_i)^2 + (Y - y_i)^2 + (Z - z_i)^2, \quad (A3)$$

$$P_i^2 = s_i^2(t_i - T)^2, \quad (A4)$$

$$\begin{aligned} s_i^2 = & \left(c_i^2 - u_i^2 - v_i^2 - w_i^2 \right) - \left[2 / (t_i - T) \right] \\ & \times \left[u_i(X - x_i) + v_i(Y - y_i) + w_i(Z - z_i) \right]. \end{aligned} \quad (A5)$$

Thus defined, the weighted range equation solution seeks those values of the unknown target coordinates and shot time (X, Y, Z, T) for which

$$\sum_{i=1}^N W_i e_i^2 = \text{minimum} . \quad (\text{A6})$$

For the purposes of this study, y_i , z_i , u_i , v_i , w_i , and Z are taken to be zero, all c_i are assumed equal to a single value (the speed of sound at an effective temperature of 10°C), and $x_{i+1} - x_i$ is assumed to be a constant, 1350 meters. Based on prior experimentation with real sound ranging data to determine the best exponent n , W_i is defined as follows:

$$W_i = R_i^n / \sum_{i=1}^N R_i^n , \quad (\text{A7})$$

$$n = -5 . \quad (\text{A8})$$

The solution to (A6) is obtained by an iterative computation, using conventional least squares methods and treating the W_i as constants during each approximation.

DISTRIBUTION LIST

Dr. Frank D. Eaton
Geophysical Institute
University of Alaska
Fairbanks, AK 99701

Commander
US Army Aviation Center
ATTN: ATZQ-D-MA
Fort Rucker, AL 36362

Chief, Atmospheric Sciences Div
Code ES-81
NASA
Marshall Space Flight Center,
AL 35812

Commander
US Army Missile R&D Command
ATTN: DRDMI-CGA (B. W. Fowler)
Redstone Arsenal, AL 35809

Redstone Scientific Information Center
ATTN: DRDMI-TBD
US Army Missile R&D Command
Redstone Arsenal, AL 35809

Commander
US Army Missile R&D Command
ATTN: DRDMI-TEM (R. Haraway)
Redstone Arsenal, AL 35809

Commander
US Army Missile R&D Command
ATTN: DRDMI-TRA (Dr. Essenwanger)
Redstone Arsenal, AL 35809

Commander
HQ, Fort Huachuca
ATTN: Tech Ref Div
Fort Huachuca, AZ 85613

Commander
US Army Intelligence Center & School
ATTN: ATSI-CD-MD
Fort Huachuca, AZ 85613

Commander
US Army Yuma Proving Ground
ATTN: Technical Library
Bldg 2100
Yuma, AZ 85364

Naval Weapons Center (Code 3173)
ATTN: Dr. A. Shlanta
China Lake, CA 93555

Sylvania Elec Sys Western Div
ATTN: Technical Reports Library
PO Box 205
Mountain View, CA 94040

Geophysics Officer
PMTC Code 3250
Pacific Missile Test Center
Point Mugu, CA 93042

Commander
Naval Ocean Systems Center (Code 4473)
ATTN: Technical Library
San Diego, CA 92152

Meteorologist in Charge
Kwajalein Missile Range
PO Box 67
APO San Francisco, 96555

Director
NOAA/ERL/APCL R31
RB3-Room 567
Boulder, CO 80302

Library-R-51-Tech Reports
NOAA/ERL
320 S. Broadway
Boulder, CO 80302

National Center for Atmos Research
NCAR Library
PO Box 3000
Boulder, CO 80307

R. B. Girardo
Bureau of Reclamation
E&R Center, Code 1220
Denver Federal Center, Bldg 67
Denver, CO 80225

National Weather Service
National Meteorological Center
W321, WWB, Room 201
ATTN: Mr. Quiroz
Washington, DC 20233

Mil Assistant for Atmos Sciences
Ofc of the Undersecretary of Defense
for Rsch & Engr/E&LS - Room 3D129
The Pentagon
Washington, DC 20301

Defense Communications Agency
Technical Library Center
Code 205
Washington, DC 20305

Director
Defense Nuclear Agency
ATTN: Technical Library
Washington, DC 20305

HQDA (DAEN-RDM/Dr. de Percin)
Washington, DC 20314

Director
Naval Research Laboratory
Code 5530
Washington, DC 20375

Commanding Officer
Naval Research Laboratory
Code 2627
Washington, DC 20375

Dr. J. M. MacCallum
Naval Research Laboratory
Code 1409
Washington, DC 20375

The Library of Congress
ATTN: Exchange & Gift Div
Washington, DC 20540
2

Head, Atmos Rsch Section
Div Atmospheric Science
National Science Foundation
1800 G. Street, NW
Washington, DC 20550

CPT Hugh Albers, Exec Sec
Interdept Committee on Atmos Science
National Science Foundation
Washington, DC 20550

Director, Systems R&D Service
Federal Aviation Administration
ATTN: ARD-54
2100 Second Street, SW
Washington, DC 20590

ADTC/DLODL
Eglin AFB, FL 32542

Naval Training Equipment Center
ATTN: Technical Library
Orlando, FL 32813

Det 11, 2WS/OI
ATTN: Maj Orondorff
Patrick AFB, FL 32925

USAFETAC/CB
Scott AFB, IL 62225

HQ, ESD/TOSI/S-22
Hanscom AFB, MA 01731

Air Force Geophysics Laboratory
ATTN: LCB (A. S. Carten, Jr.)
Hanscom AFB, MA 01731

Air Force Geophysics Laboratory
ATTN: LYD
Hanscom AFB, MA 01731

Meteorology Division
AFGL/LY
Hanscom AFB, MA 01731

US Army Liaison Office
MIT-Lincoln Lab, Library A-082
PO Box 73
Lexington, MA 02173

Director
US Army Ballistic Rsch Lab
ATTN: DRDAR-BLB (Dr. G. E. Keller)
Aberdeen Proving Ground, MD 21005

Commander
US Army Ballistic Rsch Lab
ATTN: DRDAR-BLP
Aberdeen Proving Ground, MD 21005

Director
US Army Armament R&D Command
Chemical Systems Laboratory
ATTN: DRDAR-CLJ-I
Aberdeen Proving Ground, MD 21010

Chief CB Detection & Alarms Div
Chemical Systems Laboratory
ATTN: DRDAR-CLC-CR (H. Tannenbaum)
Aberdeen Proving Ground, MD 21010

Commander
Harry Diamond Laboratories
ATTN: DELHD-CO
2800 Powder Mill Road
Adelphi, MD 20783

Commander
ERADCOM
ATTN: DRDEL-AP
2800 Powder Mill Road
Adelphi, MD 20783
2

Commander
ERADCOM
ATTN: DRDEL-CG/DRDEL-DC/DRDEL-CS
2800 Powder Mill Road
Adelphi, MD 20783

Commander
ERADCOM
ATTN: DRDEL-CT
2800 Powder Mill Road
Adelphi, MD 20783

Commander
ERADCOM
ATTN: DRDEL-EA
2800 Powder Mill Road
Adelphi, MD 20783

Commander
ERADCOM
ATTN: DRDEL-PA/DRDEL-ILS/DRDEL-E
2800 Powder Mill Road
Adelphi, MD 20783

Commander
ERADCOM
ATTN: DRDEL-PAO (S. Kimmel)
2800 Powder Mill Road
Adelphi, MD 20783

Chief
Intelligence Materiel Dev & Support Ofc
ATTN: DELEW-WL-I
Bldg 4554
Fort George G. Meade, MD 20755

Acquisitions Section, IRDB-D823
Library & Info Service Div, NOAA
6009 Executive Blvd
Rockville, MD 20852

Naval Surface Weapons Center
White Oak Library
Silver Spring, MD 20910

The Environmental Research
Institute of MI
ATTN: IRIA Library
PO Box 8618
Ann Arbor, MI 48107

Mr. William A. Main
USDA Forest Service
1407 S. Harrison Road
East Lansing, MI 48823

Dr. A. D. Belmont
Research Division
PO Box 1249
Control Data Corp
Minneapolis, MN 55440

Director
Naval Oceanography & Meteorology
NSTL Station
Bay St Louis, MS 39529

Director
US Army Engr Waterways Experiment Sta
ATTN: Library
PO Box 631
Vicksburg, MS 39180

Environmental Protection Agency
Meteorology Laboratory
Research Triangle Park, NC 27711

US Army Research Office
ATTN: DRXRO-PP
PO Box 12211
Research Triangle Park, NC 27709

Commanding Officer
US Army Armament R&D Command
ATTN: DRDAR-TSS Bldg 59
Dover, NJ 07801

Commander
HQ, US Army Avionics R&D Activity
ATTN: DAVAA-O
Fort Monmouth, NJ 07703

Commander/Director
US Army Combat Surveillance & Target
Acquisition Laboratory
ATTN: DELCS-D
Fort Monmouth, NJ 07703

Commander
US Army Electronics R&D Command
ATTN: DELCS-S
Fort Monmouth, NJ 07703

US Army Materiel Systems
Analysis Activity
ATTN: DRXSY-MP
Aberdeen Proving Ground, MD 21005

Director
US Army Electronics Technology &
Devices Laboratory
ATTN: DELET-D
Fort Monmouth, NJ 07703

Commander
US Army Electronic Warfare Laboratory
ATTN: DELEW-D
Fort Monmouth, NJ 07703

Commander
US Army Night Vision &
Electro-Optics Laboratory
ATTN: DELNV-L (Dr. Rudolf Buser)
Fort Monmouth, NJ 07703

Commander
ERADCOM Technical Support Activity
ATTN: DELSD-L
Fort Monmouth, NJ 07703

Project Manager, FIREFINDER
ATTN: DRCPM-FF
Fort Monmouth, NJ 07703

Project Manager, REMBASS
ATTN: DRCPM-RBS
Fort Monmouth, NJ 07703

Commander
US Army Satellite Comm Agency
ATTN: DRCPM-SC-3
Fort Monmouth, NJ 07703

Commander
ERADCOM Scientific Advisor
ATTN: DRDEL-SA
Fort Monmouth, NJ 07703

6585 TG/WE
Holloman AFB, NM 88330

AFWL/WE
Kirtland, AFB, NM 87117

AFWL/Technical Library (SUL)
Kirtland AFB, NM 87117

Commander
US Army Test & Evaluation Command
ATTN: STEWS-AD-L
White Sands Missile Range, NM 88002

Rome Air Development Center
ATTN: Documents Library
TSLD (Bette Smith)
Griffiss AFB, NY 13441

Commander
US Army Tropic Test Center
ATTN: STETC-TD (Info Center)
APO New York 09827

Commandant
US Army Field Artillery School
ATTN: ATSF-CD-R (Mr. Farmer)
Fort Sill, OK 73503

Commandant
US Army Field Artillery School
ATTN: ATSF-CF-R
Fort Sill, OK 73503

Director CFD
US Army Field Artillery School
ATTN: Met Division
Fort Sill, OK 73503

Commandant
US Army Field Artillery School
ATTN: Morris Swett Library
Fort Sill, OK 73503

Commander
US Army Dugway Proving Ground
ATTN: MT-DA-L
Dugway, UT 84022

Dr. C. R. Sreedrahan
Research Associates
Utah State University, UNC 48
Logan, UT 84322

Inge Dirmhirn, Professor
Utah State University, UNC 48
Logan, UT 84322

Defense Documentation Center
ATTN: DDC-TCA
Cameron Station Bldg 5
Alexandria, VA 22314
12

Commanding Officer
US Army Foreign Sci & Tech Center
ATTN: DRXST-IS1
220 7th Street, NE
Charlottesville, VA 22901

Naval Surface Weapons Center
Code G65
Dahlgren, VA 22448

Commander
US Army Night Vision
& Electro-Optics Lab
ATTN: DELNV-D
Fort Belvoir, VA 22060

Commander and Director
US Army Engineer Topographic Lab
ETL-TD-MB
Fort Belvoir, VA 22060

Director
Applied Technology Lab
DAVDL-EU-TSD
ATTN: Technical Library
Fort Eustis, VA 23604

Department of the Air Force
OL-C, 5WW
Fort Monroe, VA 23651

Department of the Air Force
5WW/DN
Langley AFB, VA 23665

Director
Development Center MCDEC
ATTN: Firepower Division
Quantico, VA 22134

US Army Nuclear & Chemical Agency
ATTN: MONA-WE
Springfield, VA 22150

Director
US Army Signals Warfare Laboratory
ATTN: DELSW-OS (Dr. R. Burkhardt)
Vint Hill Farms Station
Warrenton, VA 22186

Commander
US Army Cold Regions Test Center
ATTN: STECR-OP-PM
APO Seattle, WA 98733

Dr. John L. Walsh
Code 5560
Navy Research Lab
Washington, DC 20375

Commander
TRASANA
ATTN: ATAA-PL
(Dolores Anguiano)
White Sands Missile Range, NM 88002

Commander
US Army Dugway Proving Ground
ATTN: STEDP-MT-DA-M (Mr. Paul Carlson)
Dugway, UT 84022

Commander
US Army Dugway Proving Ground
ATTN: STEDP-MT-DA-T
(Mr. William Peterson)
Dugway, UT 84022

Commander
USATRADO
ATTN: ATCD-SIE
Fort Monroe, VA 23651

Commander
USATRADO
ATTN: ATCD-CF
Fort Monroe, VA 23651

Commander
USATRADO
ATTN: Tech Library
Fort Monroe, VA 23651

ATMOSPHERIC SCIENCES RESEARCH PAPERS

1. Lindberg, J.D., "An Improvement to a Method for Measuring the Absorption Coefficient of Atmospheric Dust and other Strongly Absorbing Powders," ECOM-5565, July 1975.
2. Avara, Elton P., "Mesoscale Wind Shears Derived from Thermal Winds," ECOM-5566, July 1975.
3. Gomez, Richard B., and Joseph H. Pierluissi, "Incomplete Gamma Function Approximation for King's Strong-Line Transmittance Model," ECOM-5567, July 1975.
4. Blanco, A.J., and B.F. Engebos, "Ballistic Wind Weighting Functions for Tank Projectiles," ECOM-5568, August 1975.
5. Taylor, Fredrick J., Jack Smith, and Thomas H. Pries, "Crosswind Measurements through Pattern Recognition Techniques," ECOM-5569, July 1975.
6. Walters, D.L., "Crosswind Weighting Functions for Direct-Fire Projectiles," ECOM-5570, August 1975.
7. Duncan, Louis D., "An Improved Algorithm for the Iterated Minimal Information Solution for Remote Sounding of Temperature," ECOM-5571, August 1975.
8. Robbiani, Raymond L., "Tactical Field Demonstration of Mobile Weather Radar Set AN/TPS-41 at Fort Rucker, Alabama," ECOM-5572, August 1975.
9. Miers, B., G. Blackman, D. Langer, and N. Lorimier, "Analysis of SMS/GOES Film Data," ECOM-5573, September 1975.
10. Manquero, Carlos, Louis Duncan, and Rufus Bruce, "An Indication from Satellite Measurements of Atmospheric CO₂ Variability," ECOM-5574, September 1975.
11. Petracca, Carmine, and James D. Lindberg, "Installation and Operation of an Atmospheric Particulate Collector," ECOM-5575, September 1975.
12. Avara, Elton P., and George Alexander, "Empirical Investigation of Three Iterative Methods for Inverting the Radiative Transfer Equation," ECOM-5576, October 1975.
13. Alexander, George D., "A Digital Data Acquisition Interface for the SMS Direct Readout Ground Station — Concept and Preliminary Design," ECOM-5577, October 1975.
14. Cantor, Israel, "Enhancement of Point Source Thermal Radiation Under Clouds in a Nonattenuating Medium," ECOM-5578, October 1975.
15. Norton, Colburn, and Glenn Hoidale, "The Diurnal Variation of Mixing Height by Month over White Sands Missile Range, N.M.," ECOM-5579, November 1975.
16. Avara, Elton P., "On the Spectrum Analysis of Binary Data," ECOM-5580, November 1975.
17. Taylor, Fredrick J., Thomas H. Pries, and Chao-Huan Huang, "Optimal Wind Velocity Estimation," ECOM-5581, December 1975.
18. Avara, Elton P., "Some Effects of Autocorrelated and Cross-Correlated Noise on the Analysis of Variance," ECOM-5582, December 1975.
19. Gillespie, Patti S., R.L. Armstrong, and Kenneth O. White, "The Spectral Characteristics and Atmospheric CO₂ Absorption of the Ho³⁺ YLF Laser at 2.05 μ m," ECOM-5583, December 1975.
20. Novlan, David J., "An Empirical Method of Forecasting Thunderstorms for the White Sands Missile Range," ECOM-5584, February 1976.
21. Avara, Elton P., "Randomization Effects in Hypothesis Testing with Autocorrelated Noise," ECOM-5585, February 1976.
22. Watkins, Wendell R., "Improvements in Long Path Absorption Cell Measurement," ECOM-5586, March 1976.
23. Thomas, Joe, George D. Alexander, and Marvin Dubbin, "SATTEL — An Army Dedicated Meteorological Telemetry System," ECOM-5587, March 1976.
24. Kennedy, Bruce W., and Delbert Bynum, "Army User Test Program for the RDT&E-XM-75 Meteorological Rocket," ECOM-5588, April 1976.

25. Barnett, Kenneth M., "A Description of the Artillery Meteorological Comparisons at White Sands Missile Range, October 1974 - December 1974 ('PASS' - Prototype Artillery [Meteorological] Subsystem)," ECOM-5589, April 1976.
26. Miller, Walter B., "Preliminary Analysis of Fall-of-Shot From Project 'PASS'," ECOM-5590, April 1976.
27. Avara, Elton P., "Error Analysis of Minimum Information and Smith's Direct Methods for Inverting the Radiative Transfer Equation," ECOM-5591, April 1976.
28. Yee, Young P., James D. Horn, and George Alexander, "Synoptic Thermal Wind Calculations from Radiosonde Observations Over the Southwestern United States," ECOM-5592, May 1976.
29. Duncan, Louis D., and Mary Ann Seagraves, "Applications of Empirical Corrections to NOAA-4 VTPR Observations," ECOM-5593, May 1976.
30. Miers, Bruce T., and Steve Weaver, "Applications of Meteorological Satellite Data to Weather Sensitive Army Operations," ECOM-5594, May 1976.
31. Sharenow, Moses, "Redesign and Improvement of Balloon ML-566," ECOM-5595, June, 1976.
32. Hansen, Frank V., "The Depth of the Surface Boundary Layer," ECOM-5596, June 1976.
33. Pinnick, R.G., and E.B. Stenmark, "Response Calculations for a Commercial Light-Scattering Aerosol Counter," ECOM-5597, July 1976.
34. Mason, J., and G.B. Hoidale, "Visibility as an Estimator of Infrared Transmittance," ECOM-5598, July 1976.
35. Bruce, Rufus E., Louis D. Duncan, and Joseph H. Pierluissi, "Experimental Study of the Relationship Between Radiosonde Temperatures and Radiometric-Area Temperatures," ECOM-5599, August 1976.
36. Duncan, Louis D., "Stratospheric Wind Shear Computed from Satellite Thermal Sounder Measurements," ECOM-5800, September 1976.
37. Taylor, F., P. Mohan, P. Joseph and T. Pries, "An All Digital Automated Wind Measurement System," ECOM-5801, September 1976.
38. Bruce, Charles, "Development of Spectrophones for CW and Pulsed Radiation Sources," ECOM-5802, September 1976.
39. Duncan, Louis D., and Mary Ann Seagraves, "Another Method for Estimating Clear Column Radiances," ECOM-5803, October 1976.
40. Blanco, Abel J., and Larry E. Taylor, "Artillery Meteorological Analysis of Project Pass," ECOM-5804, October 1976.
41. Miller, Walter, and Bernard Engebos, "A Mathematical Structure for Refinement of Sound Ranging Estimates," ECOM-5805, November, 1976.
42. Gillespie, James B., and James D. Lindberg, "A Method to Obtain Diffuse Reflectance Measurements from 1.0 to 3.0 μm Using a Cary 171 Spectrophotometer," ECOM-5806, November 1976.
43. Rubio, Roberto, and Robert O. Olsen, "A Study of the Effects of Temperature Variations on Radio Wave Absorption," ECOM-5807, November 1976.
44. Ballard, Harold N., "Temperature Measurements in the Stratosphere from Balloon-Borne Instrument Platforms, 1968-1975," ECOM-5808, December 1976.
45. Monahan, H.H., "An Approach to the Short-Range Prediction of Early Morning Radiation Fog," ECOM-5809, January 1977.
46. Engebos, Bernard Francis, "Introduction to Multiple State Multiple Action Decision Theory and Its Relation to Mixing Structures," ECOM-5810, January 1977.
47. Low, Richard D.H., "Effects of Cloud Particles on Remote Sensing from Space in the 10-Micrometer Infrared Region," ECOM-5811, January 1977.
48. Bonner, Robert S., and R. Newton, "Application of the AN/GVS-5 Laser Rangefinder to Cloud Base Height Measurements," ECOM-5812, February 1977.
49. Rubio, Roberto, "Lidar Detection of Subvisible Reentry Vehicle Erosive Atmospheric Material," ECOM-5813, March 1977.
50. Low, Richard D.H., and J.D. Horn, "Mesoscale Determination of Cloud-Top Height: Problems and Solutions," ECOM-5814, March 1977.

51. Duncan, Louis D., and Mary Ann Seagraves, "Evaluation of the NOAA-4 VTPR Thermal Winds for Nuclear Fallout Predictions," ECOM-5815, March 1977.
52. Randhawa, Jagir S., M. Izquierdo, Carlos McDonald and Zvi Salpeter, "Stratospheric Ozone Density as Measured by a Chemiluminescent Sensor During the Stratcom VI-A Flight," ECOM-5816, April 1977.
53. Rubio, Roberto, and Mike Izquierdo, "Measurements of Net Atmospheric Irradiance in the 0.7- to 2.8-Micrometer Infrared Region," ECOM-5817, May 1977.
54. Ballard, Harold N., Jose M. Serna, and Frank P. Hudson Consultant for Chemical Kinetics, "Calculation of Selected Atmospheric Composition Parameters for the Mid-Latitude, September Stratosphere," ECOM-5818, May 1977.
55. Mitchell, J.D., R.S. Sagar, and R.O. Olsen, "Positive Ions in the Middle Atmosphere During Sunrise Conditions," ECOM-5819, May 1977.
56. White, Kenneth O., Wendell R. Watkins, Stuart A. Schleusener, and Ronald L. Johnson, "Solid-State Laser Wavelength Identification Using a Reference Absorber," ECOM-5820, June 1977.
57. Watkins, Wendell R., and Richard G. Dixon, "Automation of Long-Path Absorption Cell Measurements," ECOM-5821, June 1977.
58. Taylor, S.E., J.M. Davis, and J.B. Mason, "Analysis of Observed Soil Skin Moisture Effects on Reflectance," ECOM-5822, June 1977.
59. Duncan, Louis D. and Mary Ann Seagraves, "Fallout Predictions Computed from Satellite Derived Winds," ECOM-5823, June 1977.
60. Snider, D.E., D.G. Murcray, F.H. Murcray, and W.J. Williams, "Investigation of High-Altitude Enhanced Infrared Background Emissions" (U), SECRET, ECOM-5824, June 1977.
61. Dubbin, Marvin H. and Dennis Hall, "Synchronous Meteorological Satellite Direct Readout Ground System Digital Video Electronics," ECOM-5825, June 1977.
62. Miller, W., and B. Engebos, "A Preliminary Analysis of Two Sound Ranging Algorithms," ECOM-5826, July 1977.
63. Kennedy, Bruce W., and James K. Luers, "Ballistic Sphere Techniques for Measuring Atmospheric Parameters," ECOM-5827, July 1977.
64. Duncan, Louis D., "Zenith Angle Variation of Satellite Thermal Sounder Measurements," ECOM-5828, August 1977.
65. Hansen, Frank V., "The Critical Richardson Number," ECOM-5829, September 1977.
66. Ballard, Harold N., and Frank P. Hudson (Compilers), "Stratospheric Composition Balloon-Borne Experiment," ECOM-5830, October 1977.
67. Barr, William C., and Arnold C. Peterson, "Wind Measuring Accuracy Test of Meteorological Systems," ECOM-5831, November 1977.
68. Ethridge, G.A. and F.V. Hansen, "Atmospheric Diffusion: Similarity Theory and Empirical Derivations for Use in Boundary Layer Diffusion Problems," ECOM-5832, November 1977.
69. Low, Richard D.H., "The Internal Cloud Radiation Field and a Technique for Determining Cloud Blackness," ECOM-5833, December 1977.
70. Watkins, Wendell R., Kenneth O. White, Charles W. Bruce, Donald L. Walters, and James D. Lindberg, "Measurements Required for Prediction of High Energy Laser Transmission," ECOM-5834, December 1977.
71. Rubio, Robert, "Investigation of Abrupt Decreases in Atmospherically Backscattered Laser Energy," ECOM-5835, December 1977.
72. Monahan, H.H. and R.M. Cionco, "An Interpretative Review of Existing Capabilities for Measuring and Forecasting Selected Weather Variables (Emphasizing Remote Means)," ASL-TR-0001, January 1978.
73. Heaps, Melvin G., "The 1979 Solar Eclipse and Validation of D-Region Models," ASL-TR-0002, March 1978.

74. Jennings, S.G., and J.B. Gillespie, "M.I.E. Theory Sensitivity Studies - The Effects of Aerosol Complex Refractive Index and Size Distribution Variations on Extinction and Absorption Coefficients Part II: Analysis of the Computational Results," ASL-TR-0003, March 1978.
75. White, Kenneth O. et al, "Water Vapor Continuum Absorption in the 3.5 μ m to 4.0 μ m Region," ASL-TR-0004, March 1978.
76. Olsen, Robert O., and Bruce W. Kennedy, "ABRES Pretest Atmospheric Measurements," ASL-TR-0005, April 1978.
77. Ballard, Harold N., Jose M. Serna, and Frank P. Hudson, "Calculation of Atmospheric Composition in the High Latitude September Stratosphere," ASL-TR-0006, May 1978.
78. Watkins, Wendell R. et al, "Water Vapor Absorption Coefficients at HF Laser Wavelengths," ASL-TR-0007, May 1978.
79. Hansen, Frank V., "The Growth and Prediction of Nocturnal Inversions," ASL-TR-0008, May 1978.
80. Samuel, Christine, Charles Bruce, and Ralph Brewer, "Spectrophone Analysis of Gas Samples Obtained at Field Site," ASL-TR-0009, June 1978.
81. Pinnick, R.G. et al., "Vertical Structure in Atmospheric Fog and Haze and its Effects on IR Extinction," ASL-TR-0010, July 1978.
82. Low, Richard D.H., Louis D. Duncan, and Richard B. Gomez, "The Microphysical Basis of Fog Optical Characterization," ASL-TR-0011, August 1978.
83. Heaps, Melvin G., "The Effect of a Solar Proton Event on the Minor Neutral Constituents of the Summer Polar Mesosphere," ASL-TR-0012, August 1978.
84. Mason, James B., "Light Attenuation in Falling Snow," ASL-TR-0013, August 1978.
85. Blanco, Abel J., "Long-Range Artillery Sound Ranging: "PASS" Meteorological Application," ASL-TR-0014, September 1978.
86. Heaps, M.G., and F.E. Niles, "Modeling the Ion Chemistry of the D-Region: A case Study Based Upon the 1966 Total Solar Eclipse," ASL-TR-0015, September 1978.
87. Jennings, S.G., and R.G. Pinnick, "Effects of Particulate Complex Refractive Index and Particle Size Distribution Variations on Atmospheric Extinction and Absorption for Visible Through Middle-Infrared Wavelengths," ASL-TR-0016, September 1978.
88. Watkins, Wendell R., Kenneth O. White, Lanny R. Bower, and Brian Z. Sojka, "Pressure Dependence of the Water Vapor Continuum Absorption in the 3.5- to 4.0-Micrometer Region," ASL-TR-0017, September 1978.
89. Miller, W.B., and B.F. Engebos, "Behavior of Four Sound Ranging Techniques in an Idealized Physical Environment," ASL-TR-0018, September 1978.
90. Gomez, Richard G., "Effectiveness Studies of the CBU-88/B Bomb, Cluster, Smoke Weapon" (U), CONFIDENTIAL ASL-TR-0019, September 1978.
91. Miller, August, Richard C. Shirkey, and Mary Ann Seagraves, "Calculation of Thermal Emission from Aerosols Using the Doubling Technique," ASL-TR-0020, November, 1978.
92. Lindberg, James D. et al., "Measured Effects of Battlefield Dust and Smoke on Visible, Infrared, and Millimeter Wavelengths Propagation: A Preliminary Report on Dusty Infrared Test-I (DIRT-I)," ASL-TR-0021, January 1979.
93. Kennedy, Bruce W., Arthur Kinghorn, and B.R. Hixon, "Engineering Flight Tests of Range Meteorological Sounding System Radiosonde," ASL-TR-0022, February 1979.
94. Rubio, Roberto, and Don Hooek, "Microwave Effective Earth Radius Factor Variability at Wiesbaden and Balboa," ASL-TR-0023, February 1979.
95. Low, Richard D.H., "A Theoretical Investigation of Cloud/Fog Optical Properties and Their Spectral Correlations," ASL-TR-0024, February 1979.

96. Pinnick, R.G., and H. J. Auvermann, "Response Characteristics of Knollenberg Light-Scattering Aerosol Counters," ASL-TR-0025, February 1979.
97. Heaps, Melvin G., Robert O. Olsen, and Warren W. Berning, "Solar Eclipse 1979, Atmospheric Sciences Laboratory Program Overview," ASL-TR-0026 February 1979.
98. Blanco, Abel J., "Long-Range Artillery Sound Ranging: 'PASS' GR-8 Sound Ranging Data," ASL-TR-0027, March 1979.
99. Kennedy, Bruce W., and Jose M. Serna, "Meteorological Rocket Network System Reliability," ASL-TR-0028, March 1979.
100. Swingle, Donald M., "Effects of Arrival Time Errors in Weighted Range Equation Solutions for Linear Base Sound Ranging," ASL-TR-0029, April 1979.